

KMVT How-To Guide

How to operate the audio board – 11/11/14



You will need:

- Fingers to turn knobs
- Ears to listen
- And Eyes to see

Control room volume is adjusted by the knob pictured in image #11. It is located above the audio patch panel.

1. Zero the board
 - a. Zeroing a board means to set everything to its default settings
 - b. Reference images below shows where everything should be. Images 1-6
2. Locate where each input you are receiving is
 - a. Either check the studio panel inputs or perform a mic check
 - b. Label Each input with tape and a pencil
 - c. Press the L-R button for each channel that you are using. (Image #9)
3. Perform mic checks
 - a. Set the channel slider to U. (Image #7)
 - b. Set the main slider to U. (Image #10)
 - c. Have the talent begin speaking or singing at the same level that they will during the performance
 - d. Adjust the gain knob (Image #8) until the VU meter (Image #5) peaks just above zero on average
 - e. Mute that channel
 - f. Move to the next input
4. Prepare for the start of the show
 - a. Prepare any tape/CD to the correct track for playback
 - b. Set all b-roll and tape/CD channel sliders to zero and unmute them
 - c. Set all microphone channel sliders to U and mute them
5. The show begins
 - a. Mute and unmute microphones as needed
 - b. Use sliders to bring in and out any b-roll or music audio
 - c. Use sliders to adjust audio level during the show

6. The show is over
 - a. Reset the audio Board to the default settings. (Images #1-6)

Notes: This document is intended to cover a specific task. In many cases you may need additional skills to complete the project. Please refer to one of our other How-To Guides or consider enrolling in one of our training courses for more advanced training.

Image #1



Image #2



Image #3



Image #4



Image #5



Image #6



Image #7




Image #8



Image #9



Image #10



Image #11

